

## AN211

### Migrating from FM24CL16 to FM24CL16B

**Author:** Girija Chougala

**Associated Project:** No

**Associated Part Family:** FM24CL16, FM24CL16B

**Software Version:** None

**Related Documents:** For a complete list, [click here](#)

AN211 discusses the key differences which need to be considered when migrating from FM24CL16 to FM24CL16B. FM24CL16 is now obsolete and this application note explains how FM24CL16B is a replacement for FM24CL16.

### Introduction

FM24CL16B, a 16-Kbit I<sup>2</sup>C F-RAM™, is a replacement device for FM24CL16, which is now obsolete. The two devices are identical in terms of pinout, read/write functionality, Write Protect operation and address pin functionality. This application note discusses the key differences between the two devices that need to be considered when migrating from FM24CL16 to FM24CL16B.

### Drop-In Replacement or Not?

From a software point of view, the two devices are identical. From a hardware point of view, FM24CL16B has slightly higher standby current compared to FM24CL16. Additionally, FM24CL16B datasheet adds a power-up and power-down ramp rate specification of 30 μs / V and a power-up to first-access specification of 1 ms. Also, the footprint for the TDFN package of the FM24CL16B is different compared to that of FM24CL16 and hence would need hardware change when migrating.

### Ordering Part Numbers

[Table 2](#) gives the recommended FM24CL16B ordering part numbers that correspond to the now obsolete FM24CL16 ordering part numbers.

Table 2. Recommended Ordering Part Numbers for Migration

FM24CL16		FM24CL16B		Comments
Ordering Part Number	Status	Ordering Part Number	Status	
FM24CL16-G	Obsolete	FM24CL16B-G	In production	No hardware or software change is required.
FM24CL16-GTR		FM24CL16B-GTR		
FM24CL16-DG	Obsolete	FM24CL16B-DG	In production	Hardware change is required.
FM24CL16-DGTR		FM24CL16B-DGTR		

[Table 1](#) shows the compatibility chart of FM24CL16 and FM24CL16B. For a detailed comparison, see [Table 3](#).

Table 1. Compatibility Chart

FM24CL16 Feature or Spec	Is FM24CL16B compatible?
Package	Yes (SOIC) No (TDFN)
Pinout	Yes
Temperature Range	Yes
Operating Voltage	Yes
Operating Current	Yes
Standby Current	No
Read / Write Function	Yes
Timing / Frequency	Yes
Data Retention	Refer to <a href="#">Table 3</a>
Endurance	Yes

## Comparison of FM24CL16 and FM24CL16B

Table 3 gives a detailed comparison of the two devices.

Table 3. Detailed Comparison

	FM24CL16	FM24CL16B	Comments
Package Types	-G, -DG	-G, -DG	Identical “green” SOIC package, different “Green” TDFN package
Package Outlines	SOIC-8, TDFN-8 (3 mm x 6.4 mm)	SOIC-8, TDFN-8 (4 mm x 4.5 mm)	Package outline and board footprint are Identical for SOIC but different for TDFN
Pinout	-	-	Identical
Temperature Range	-40 °C to +85 °C	-40 °C to +85 °C	Identical
Operating Voltage Range	2.7 V to 3.65 V	2.0 V to 3.65 V	FM24CL16B offers a wider operating range
Active Supply Current	75 $\mu$ A @ 100 kHz 450 $\mu$ A @ 1 MHz	100 $\mu$ A @ 100 kHz 300 $\mu$ A @ 1 MHz	FM24CL16B offers lower active current at 1 MHz
Standby Current	1 $\mu$ A (max)	6 $\mu$ A (max) 3 $\mu$ A (typical)	FM24CL16B has higher standby current
Read / Write Function	-	-	Identical 1-byte addressing, Identical Slave IDs
Clock Frequency	1 MHz	1 MHz	Identical
Data Retention	45 years (+85 °C)	10 years (+85 °C) 38 years (+75 °C) 151 years (+65 °C)	Data retention is lower
Endurance (Write/Read Cycles)	Unlimited	1E+14	FM24CL16B’s endurance is large enough to be considered as unlimited for all practical applications. For a 64-byte loop, at 1 MHz, FM24CL16B’s endurance is 1700 years.
V <sub>DD</sub> Power-Up Ramp Rate (t <sub>VR</sub> )	-	30 $\mu$ s / V	Power-up ramp rate should be slower than 30 $\mu$ s / V for FM24CL16B
V <sub>DD</sub> Power-Down Ramp Rate (t <sub>VF</sub> )	-	30 $\mu$ s / V	Power-down ramp rate should be slower than 30 $\mu$ s / V for FM24CL16B
Power-Up to First Access (t <sub>PU</sub> )	-	1 ms	After power-up, the first access of FM24CL16B should be after 1 ms

## Critical Considerations

You should consider all the parameter differences mentioned in Table 3 during the migration to FM24C16B. This section discusses the critical differences. System designers should also review the [datasheet](#) when migrating to the new part.

### Package Outline

Both FM24CL16 and FM24CL16B are offered in SOIC and TDFN packages. While the SOIC package dimensions are identical, there is a difference in TDFN package dimensions. The FM24CL16 package dimensions are 3 mm x 6.4 mm and the FM24CL16B package dimensions are 4 mm x 4.5 mm. Hence the package footprints will be different. Though the package type (-DG) is identical for the two devices, this difference in package footprints should be considered during migration.

### V<sub>DD</sub> Ramp Rate

V<sub>DD</sub> power-up and power-down ramp rate specifications are added in FM24CL16B device. Ensure that the power-up and power-down ramp rates are slower than 30  $\mu$ s / V in your system.

## Power-Up to First Access

Power-up to first access specification is added in FM24CL16B device. Ensure that the FM24CL16B device is accessed only after 1 ms from power-up.

## Summary

AN211 discussed the differences between FM24CL16 and FM24CL16B which need to be considered during migration.

## Related Documents

### Datasheet

[FM24CL16B: 16-Kbit \(2 K × 8\) Serial \(I<sup>2</sup>C\) F-RAM datasheet](#)

## Document History

Document Title: Migrating from FM24CL16 to FM24CL16B - AN211

Document Number: 001-86817

Revision	ECN	Orig. of Change	Submission Date	Description of Change
**	3944550	GVCH	03/26/2013	New Spec.
*A	4278231	MEDU	03/07/2014	<p>Updated to Cypress Template.</p> <p>Updated Active Supply Current for FM24CL16 from "70 <math>\mu</math>A @ 100 kHz, 400 <math>\mu</math>A @ 1 MHz" to "75 <math>\mu</math>A @ 100 kHz, 450 <math>\mu</math>A @ 1 MHz".</p> <p>Added data retention spec to FM24CL16B at 85 °C.</p> <p>Updated "Power-up to First Access" for FM24CL16B from 10 ms to 1 ms.</p> <p>Updated "V<sub>DD</sub> Power-down Ramp Rate" for FM24CL16B from 100 <math>\mu</math>s / V to 30 <math>\mu</math>s / V.</p> <p>Removed V<sub>IH</sub>(max) spec from Table 2.</p>
*B	4498650	GVCH	09/10/2014	<p>Changed title from "Differences between FM24CL16 and FM24CL16B" to "Migrating from FM24CL16 to FM24CL16B."</p> <p>Updated abstract.</p> <p>Added "<a href="#">Ordering Part Numbers</a>" section.</p> <p>Added title for <a href="#">Table 3</a>.</p> <p>Added "<a href="#">Related Documents</a>" section.</p>

## Worldwide Sales and Design Support

Cypress maintains a worldwide network of offices, solution centers, manufacturer's representatives, and distributors. To find the office closest to you, visit us at [Cypress Locations](#).

### Products

Automotive	<a href="http://cypress.com/go/automotive">cypress.com/go/automotive</a>
Clocks & Buffers	<a href="http://cypress.com/go/clocks">cypress.com/go/clocks</a>
Interface	<a href="http://cypress.com/go/interface">cypress.com/go/interface</a>
Lighting & Power Control	<a href="http://cypress.com/go/powerpsoc">cypress.com/go/powerpsoc</a> <a href="http://cypress.com/go/plc">cypress.com/go/plc</a>
Memory	<a href="http://cypress.com/go/memory">cypress.com/go/memory</a>
PSoC	<a href="http://cypress.com/go/psoc">cypress.com/go/psoc</a>
Touch Sensing	<a href="http://cypress.com/go/touch">cypress.com/go/touch</a>
USB Controllers	<a href="http://cypress.com/go/usb">cypress.com/go/usb</a>
Wireless/RF	<a href="http://cypress.com/go/wireless">cypress.com/go/wireless</a>

### PSoC® Solutions

[psoc.cypress.com/solutions](http://psoc.cypress.com/solutions)

[PSoC 1](#) | [PSoC 3](#) | [PSoC 4](#) | [PSoC 5LP](#)

### Cypress Developer Community

[Community](#) | [Forums](#) | [Blogs](#) | [Video](#) | [Training](#)

### Technical Support

[cypress.com/go/support](http://cypress.com/go/support)

PSoC is a registered trademark of Cypress Semiconductor Corp. All other trademarks or registered trademarks referenced herein are the property of their respective owners.



Cypress Semiconductor    Phone : 408-943-2600  
198 Champion Court    Fax : 408-943-4730  
San Jose, CA 95134-1709    Website : [www.cypress.com](http://www.cypress.com)

© Cypress Semiconductor Corporation, 2013-2014. The information contained herein is subject to change without notice. Cypress Semiconductor Corporation assumes no responsibility for the use of any circuitry other than circuitry embodied in a Cypress product. Nor does it convey or imply any license under patent or other rights. Cypress products are not warranted nor intended to be used for medical, life support, life saving, critical control or safety applications, unless pursuant to an express written agreement with Cypress. Furthermore, Cypress does not authorize its products for use as critical components in life-support systems where a malfunction or failure may reasonably be expected to result in significant injury to the user. The inclusion of Cypress products in life-support systems application implies that the manufacturer assumes all risk of such use and in doing so indemnifies Cypress against all charges.

This Source Code (software and/or firmware) is owned by Cypress Semiconductor Corporation (Cypress) and is protected by and subject to worldwide patent protection (United States and foreign), United States copyright laws and international treaty provisions. Cypress hereby grants to licensee a personal, non-exclusive, non-transferable license to copy, use, modify, create derivative works of, and compile the Cypress Source Code and derivative works for the sole purpose of creating custom software and or firmware in support of licensee product to be used only in conjunction with a Cypress integrated circuit as specified in the applicable agreement. Any reproduction, modification, translation, compilation, or representation of this Source Code except as specified above is prohibited without the express written permission of Cypress.

Disclaimer: CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS MATERIAL, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. Cypress reserves the right to make changes without further notice to the materials described herein. Cypress does not assume any liability arising out of the application or use of any product or circuit described herein. Cypress does not authorize its products for use as critical components in life-support systems where a malfunction or failure may reasonably be expected to result in significant injury to the user. The inclusion of Cypress' product in a life-support systems application implies that the manufacturer assumes all risk of such use and in doing so indemnifies Cypress against all charges.

Use may be limited by and subject to the applicable Cypress software license agreement.