



Please note that Cypress is an Infineon Technologies Company.

The document following this cover page is marked as “Cypress” document as this is the company that originally developed the product. Please note that Infineon will continue to offer the product to new and existing customers as part of the Infineon product portfolio.

Continuity of document content

The fact that Infineon offers the following product as part of the Infineon product portfolio does not lead to any changes to this document. Future revisions will occur when appropriate, and any changes will be set out on the document history page.

Continuity of ordering part numbers

Infineon continues to support existing part numbers. Please continue to use the ordering part numbers listed in the datasheet for ordering.

This example uses an ADC to modify the duty cycle of a PWM, changing the brightness of the LED.

Overview

This code example uses analog input from the potentiometer on the board to modify the duty cycle of a base timer operating in PWM mode. The output pin of the PWM causes the LED to dim or brighten as the duty cycle changes.

Requirements

Tool: PSoC Creator 4.0


Programming Language: C (GCC 4.9.3)

Associated Parts: All S6E1C parts

Related Hardware: [FM0-64L-S6E1C3](#)

Design

The schematic includes the ADC and PWM components. The ADC component uses default values and no interrupts. The PWM uses the TIOA output pin to drive the green LED. The initial value of the output pin is set to high so that the LED is off by default. The timer's underflow interrupt is enabled. The interrupt handler modifies the duty cycle of the PWM when the timer reaches zero.



The firmware performs following functions:

1. Sets the pin function for the TIOA pin to be an output pin
2. Initializes and enables the ADC
3. Initializes and enables the PWM (including setting the PWM's peak count and initial duty cycle)
4. Then repeatedly starts an ADC scan and puts the result in the `duty` global variable
5. The underflow interrupt handler modifies the duty cycle every time the timer reaches zero

Design Considerations

Pin Selection

The project includes control files to automatically place the analog input and PWM output onto the appropriate pins for the supported kit hardware. To change the pin selection, delete the control file or over-ride the control file selections in the Design Wide Resources Pin Editor.

PDL Installation

The project assumes that you have installed the PDL in the location specified in the **Project Management** panel of the **Tools > Options** dialog. If that location is incorrect, you will see the build error "The given PDL path is invalid. Unable to find required PDSC file." To correct this problem in a newly-created project open the **Project > Properties** dialog and enter the correct path to the PDL. To avoid the problem in projects you create in the future, make sure you put the correct path in the **Tools > Options** dialog.

Hardware Setup

Table 1 lists the pin connections required to use this code example on supported FM0+ kits.

Table 1. List of Pins

Pin	FM0-64L-S6E1C3
ADC:CH0	P10
PWM:TIOA	P3E

Components

Table 2 lists the PSoC Creator Components used in this example, as well as the hardware resources used by each.

Table 2. List of PSoC Creator Components

Component	Version	Hardware Resources
PDL_ADC	1.0	ADC block
PDL_PWM	1.0	Base timer block
PDL_GPIO	1.0	Two GPIO pins

Parameter Settings

The PDL_ADC Component uses default parameter settings, except for the item shown in Table 3.

Table 3: ADC Component Settings

Tab	Setting	Value
none	Name	ADC

The PDL_PWM Component uses default parameter settings, with the exceptions shown in Table 4.

Table 4: PWM Component Settings

Tab	Setting	Value
Basic	ConnectTIOA	True
Interrupts	bTouchNvic	True
Interrupts	bPwmUnderflowIrq	True
PWM	enPwmOutputPolarity	Initially high

Operation

Program the kit, then click the **Resume Execution** button. Turn the potentiometer on the board and observe the LED brightness change.

Related Documents

Table 5 lists relevant application notes, code examples, knowledge base articles, device and Component datasheets.

Table 5: Related Documents

PSoC Creator Component Datasheets	
PDL_BT	Supports PWM, PPG, PWC, and Reload timers, in either continuous or one-shot mode
PDL_ADC	Supports scan and priority conversions on multiple channels (right-click on the Component to access)
PDL_GPIO	Supports firmware access to physical pins (right-click on the Component to access)
Device Documentation	
S6E1C	FM0+ S6E1C-Series Ultra Low Power ARM® Cortex®-M0+ Microcontroller (MCU) Family
Development Kit (DVK) Documentation	
FM0-64L-S6E1C3	ARM® Cortex®-M0+ MCU Starter Kit with USB and Digital Audio Interface

Document History

Document Title: CE216686 - FM0+ Base Timer With ADC

Document Number: 002-16686

Revision	ECN	Orig. of Change	Submission Date	Description of Change
**	5443685	YFS	09/20/16	New Code Example.
*A	5453487	YFS	09/28/16	Changed the workspace folder name. Moved the PDF file.
*B	5823657	JETT	07/18/2017	Added search keyword so that user can quickly find Code Examples from the component instance popup menu. Updated logo and copyright date. Added FM0+ as prefix to title.
*C	5988588	YFS	12/8/17	Removed S6E1B support.

Worldwide Sales and Design Support

Cypress maintains a worldwide network of offices, solution centers, manufacturer's representatives, and distributors. To find the office closest to you, visit us at [Cypress Locations](#).

Products

ARM® Cortex® Microcontrollers	cypress.com/arm
Automotive	cypress.com/automotive
Clocks & Buffers	cypress.com/clocks
Interface	cypress.com/interface
Internet of Things	cypress.com/iot
Memory	cypress.com/memory
Microcontrollers	cypress.com/mcu
PSoC	cypress.com/psoc
Power Management ICs	cypress.com/pmic
Touch Sensing	cypress.com/touch
USB Controllers	cypress.com/usb
Wireless Connectivity	cypress.com/wireless

PSoC® Solutions

[PSoC 1](#) | [PSoC 3](#) | [PSoC 4](#) | [PSoC 5LP](#) | [PSoC 6](#)

Cypress Developer Community

[Forums](#) | [WICED IOT Forums](#) | [Projects](#) | [Videos](#) | [Blogs](#) | [Training](#) | [Components](#)

Technical Support

cypress.com/support

All other trademarks or registered trademarks referenced herein are the property of their respective owners.



Cypress Semiconductor
198 Champion Court
San Jose, CA 95134-1709

© Cypress Semiconductor Corporation, 2016-2017. This document is the property of Cypress Semiconductor Corporation and its subsidiaries, including Spansion LLC ("Cypress"). This document, including any software or firmware included or referenced in this document ("Software"), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you a personal, non-exclusive, nontransferable license (without the right to sublicense) (1) under its copyright rights in the Software (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units, and (2) under those claims of Cypress's patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely for use with Cypress hardware products. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE OR ACCOMPANYING HARDWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. To the extent permitted by applicable law, Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. Cypress products are not designed, intended, or authorized for use as critical components in systems designed or intended for the operation of weapons, weapons systems, nuclear installations, life-support devices or systems, other medical devices or systems (including resuscitation equipment and surgical implants), pollution control or hazardous substances management, or other uses where the failure of the device or system could cause personal injury, death, or property damage ("Unintended Uses"). A critical component is any component of a device or system whose failure to perform can be reasonably expected to cause the failure of the device or system, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from or related to all Unintended Uses of Cypress products. You shall indemnify and hold Cypress harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of Cypress products.

Cypress, the Cypress logo, Spansion, the Spansion logo, and combinations thereof, WICED, PSoC, CapSense, EZ-USB, F-RAM, and Traveo are trademarks or registered trademarks of Cypress in the United States and other countries. For a more complete list of Cypress trademarks, visit cypress.com. Other names and brands may be claimed as property of their respective owners.