

This application toggles an LED when the user switch is pressed.

Overview

This application simply toggles a green LED. When the user switch is pressed the LED pin is read, then the value is toggled (ON/OFF) and it is written back to the (Fast) FGPIO. This demonstrates the use of FGPIO for input and output and shows how to read the state of an output pin.

Requirements

Tool: PSoC Creator 4.0


Programming Language: C (GCC 4.9.3)

Associated Parts: All S6E1 parts

Related Hardware: [FM0-V48-S6E1A1](#) and [FM0-64L-S6E1C3](#)

Design

The schematic file includes two FGPIO components, renamed as shown below.

Green_LED 

SW 

The firmware performs following functions:

1. Initialize the LED FGPIO (off) and enable read
2. Initialize the switch FGPIO (pulled up)
3. Detect a switch press event
4. Read, toggle, and write the state of the LED pin

Design Considerations

PDL Installation

The project assumes that you have installed the PDL in the location specified in the Project Management panel of the Tools > Options dialog. If that location is incorrect you will see the build error “The given PDL path is invalid. Unable to find required PDSC file.” To correct this problem in a newly-created project open the Project > Properties dialog and enter the correct path to the PDL. To avoid the problem in projects you create in the future, make sure you put the correct path in the Tools > Options dialog.

Pin Selection

The project includes control files to automatically place the FGPIO onto the appropriate pins for the supported kit hardware. To change the pin selections, delete the control file or over-ride the control file selections in the Design Wide Resources Pin Editor.

Hardware Setup

The FGPIO are connected to the user switch (SW3 on FM0-V48-S6E1A1, SW2 on FM0-100L-S6E1B8 and FM0-64L-S6E1C3) and the green LED.

Table 1 lists the pin connections required to use this code example on FM0+ kits.

Table 1. List of Pins

Pin	FM0-V48-S6E1A1	FM0-64L-S6E1C3
Green_LED:FGPIO	P61	P3E
SW:FGPIO	P04	P30

Components

Table 2 lists the PSoC Creator Components used in this example, as well as the hardware resources used by each.

Table 2. List of PSoC Creator Components

Component	Version	Hardware Resources
PDL_FGPIO	1.0	FGPIO pin

Parameter Settings

All the components use their default parameter settings. Only the component instance names have been changed for readability.

Operation

Press the user switch repeatedly to toggle the LED on/off.

Related Documents

Table 3 lists all relevant application notes, code examples, knowledge base articles, device datasheets, and Component datasheets.

Table 3. Related Documents

PSoC Creator Component Datasheets	
PDL_GPIO	Supports firmware access to physical pins (right-click on the component to access)
Device Documentation	
S6E1A	FM0+ S6E1A-Series 5V Robust ARM® Cortex®-M0+ Microcontroller (MCU) Family
S6E1C	FM0+ S6E1C-Series Ultra Low Power ARM® Cortex®-M0+ Microcontroller (MCU) Family
Development Kit (DVK) Documentation	
FM0-V48-S6E1A1	ARM® Cortex®-M0+ FM0+ MCU Evaluation Board
FM0-64L-S6E1C3	ARM® Cortex®-M0+ MCU Starter Kit with USB and Digital Audio Interface

Document History

Document Title: CE216198 - FM0+ FGPIO Toggling LED

Document Number: 002-16198

Revision	ECN	Orig. of Change	Submission Date	Description of Change
**	5415962	YFS	08/25/16	New Code Example.
*A	5448725	YFS	9/29/16	Added workspace file.
*B	5776486	YFS	6/16/17	Added search keyword so that user can quickly find Code Examples from the component instance popup menu. Updated logo and copyright date.
*C	5987692	YFS	12/7/17	Removed S6E1B support.

Worldwide Sales and Design Support

Cypress maintains a worldwide network of offices, solution centers, manufacturer's representatives, and distributors. To find the office closest to you, visit us at [Cypress Locations](#).

Products

ARM® Cortex® Microcontrollers	cypress.com/arm
Automotive	cypress.com/automotive
Clocks & Buffers	cypress.com/clocks
Interface	cypress.com/interface
Lighting & Power Control	cypress.com/powerpsoc
Memory	cypress.com/memory
PSoC	cypress.com/psoc
Touch Sensing	cypress.com/touch
USB Controllers	cypress.com/usb
Wireless/RF	cypress.com/wireless

PSoC® Solutions

[PSoC 1](#) | [PSoC 3](#) | [PSoC 4](#) | [PSoC 5LP](#)

Cypress Developer Community

[Forums](#) | [Projects](#) | [Videos](#) | [Blogs](#) | [Training](#) | [Components](#)

Technical Support

cypress.com/support



Cypress Semiconductor Phone : 408-943-2600
198 Champion Court Fax : 408-943-4730
San Jose, CA 95134-1709 Website : www.cypress.com

© Cypress Semiconductor Corporation, 2016-2017. This document is the property of Cypress Semiconductor Corporation and its subsidiaries, including Spansion LLC ("Cypress"). This document, including any software or firmware included or referenced in this document ("Software"), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you a personal, non-exclusive, nontransferable license (without the right to sublicense) (1) under its copyright rights in the Software (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units, and (2) under those claims of Cypress's patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely for use with Cypress hardware products. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE OR ACCOMPANYING HARDWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. To the extent permitted by applicable law, Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. Cypress products are not designed, intended, or authorized for use as critical components in systems designed or intended for the operation of weapons, weapons systems, nuclear installations, life-support devices or systems, other medical devices or systems (including resuscitation equipment and surgical implants), pollution control or hazardous substances management, or other uses where the failure of the device or system could cause personal injury, death, or property damage ("Unintended Uses"). A critical component is any component of a device or system whose failure to perform can be reasonably expected to cause the failure of the device or system, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from or related to all Unintended Uses of Cypress products. You shall indemnify and hold Cypress harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of Cypress products.

Cypress, the Cypress logo, Spansion, the Spansion logo, and combinations thereof, WICED, PSoC, CapSense, EZ-USB, F-RAM, and Traveo are trademarks or registered trademarks of Cypress in the United States and other countries. For a more complete list of Cypress trademarks, visit cypress.com. Other names and brands may be claimed as property of their respective owners.