



# PSoC® Programmer 3.12.3 Release Notes

PSoC Programmer version 3.12.3

**Release Date:** December 31, 2010

Thank you for your interest in PSoC® Programmer 3.12.3. These release notes list all new features, installation requirements, supported devices and defects fixed from the previous release.

PSoC Programmer supports PSoC Creator™ and PSoC Designer™ applications as well as supporting secondary application such as the Bridge Control Panel and the Clock Programmer. PSoC Programmer provides a COM layer customers can use to create applications using Cypress hardware.

PSoC Programmer supports all PSoC architectures including PSoC® 1, PSoC 3 and PSoC 5.

## Contents

New Features and Updates for PSoC Programmer 3.12.3 .....	1
PSoC3 Checksum Programming Failure.....	2
Firmware Update for FTK3 and DVKProg Kits .....	2
Support for CY8CKit-050 Development kit.....	2
Firmware Update for increased flash write reliability .....	2
New Supported Devices.....	2
Update / Upgrade Notes .....	2
Upgrade Using Cypress Update Manager.....	2
PSoC 3 ES2 vs. ES3 Support.....	3
Coexistence with Older PSoC Programmer Releases .....	3
Defects Fixed .....	3
Known Issues.....	4
Limitations .....	4
Installation .....	5
Minimum and Recommended Requirements .....	5
Applications Dependent on a PSoC Programmer Installation.....	6
Update Instructions.....	6
Installation Notes .....	6
Device Driver Re-Installation .....	7
Further Reading .....	7
Silicon Errata.....	8

## New Features and Updates for PSoC Programmer 3.12.3

This release expands device support for the PSoC Designer 5.1 SP1 release and the PSoC Creator 1.0 Production release, which includes fixes critical defects from the PSoC Programmer 3.12 release and supports the multiple product installation support from within the CyInstaller. There were no updates to the Bridge Control Panel or Clock Programmer for this minor update

### PSoC3 Checksum Programming Failure

This release of PSoC Programmer (v3.12.3) addresses an issue found with the PSoC Programmer 3.12 Production release. A fix will be deployed with the PSoC Programmer 3.12.3 release to address the checksum failures seen with the CY8C32xx devices.

### Firmware Update for FTK3 and DVKProg Kits

This release of PSoC Programmer 3.12.3 will release a firmware update to support ES3 silicon on FTK3 and DVKProg Kits. This firmware will be downloaded to the FTK3 and DVKProg kits automatically when connecting to PSoC Programmer.

### Support for CY8CKit-050 Development kit

PSoC Programmer now supports the CY8CKit-050 development kit. Programmer now provides support through the host GUI and signed drivers.

### Firmware Update for increased flash write reliability

This release of PSoC Programmer 3.12.3 will release a firmware update to enhance the reliability of flash write procedure for PSoC 3 ES3 Silicon.

## New Supported Devices

The following table lists the new device support for PSoC Programmer 3.12.3.

Device Family	Device
CYONSFN3050	CYONSFN3050-XW07
	CYONSFN3050-XW11
	CYONSFN3050-XWTH
CY8C20xx6	CY8C20246AS-24LKXI
	CY8C20346AS-24LQXI
	CY8C20446AS-24LQXI
	CY8C20466AS-24LQXI
	CY8C20666AS-24LTXI
	CY8C20646AS-24LTXI
CY8C21x34	CY8C21434B-24LTXI
	CY8C21434B-24LQXI
	CY8C21434B-24LCXI
	CY8C21534B-24PVXI
	CY8C21334B-24PVXI
	CY8C21234B-24SXI
CY8CTMA3xx	CY8CTMA375-LQI-01
CY8CLEd0xD01	CY8CLEd01D01-56LTXQ
	CY8CLEd04D01-56LTXQ

## Update / Upgrade Notes

### Upgrade Using Cypress Update Manager

All users who installed PSoC Programmer 3.12.3 or earlier, should use the CyInstaller Update Manager to upgrade their programmer release.

### PSoC 3 ES2 vs. ES3 Support

PSoC Programmer 3.12.3 allows Hex files targeting specific silicon to be programmed into that silicon only. For example, if you generate a Hex file for ES2 revision silicon, you will not be able to program that file into ES3 devices. Warning messages are displayed if you attempt to program a Hex file into the wrong silicon revision. Make sure the tools you are using support the silicon revision you are using.

### Coexistence with Older PSoC Programmer Releases

Uninstall all releases of PSoC Programmer 3.06 and earlier before you install or update to PSoC Programmer 3.12.3.

### Defects Fixed

The following defects were fixed in this release of PSoC Programmer.

Defect	Fix and Impact	Defect
<b>Programmer Application</b>		
Programming failure with the CY8C28533-24AXI devices.	The device database was updated to fix the error.	73513
Signed Drivers for TrueTouch Bridge	Drivers have been signed for Vista and Win 7 systems.	77280
Programming issues with CY8CLED08-28PVXI devices found.	The device database was updated to fix the error.	79607
<b>Hardware</b>		
N/A	N/A	N/A
<b>Installer</b>		
N/A	N/A	N/A
<b>Documentation</b>		
N/A	N/A	N/A
<b>Bridge Control Panel</b>		
Example projects included in the Bridge Control Panel folder do not compile.	The file properties on the example projects were set to read only. This defect is fixed. Example projects should build and compile without modification.	75326
The vertical scale operation is not updating correctly when using the	The charting features have been updated to better support the pan	73850

pan feature on the graph.	feature.	
I2C speed and voltage selections should be retained.	Implemented auto saving of last Clock and VCC selections.	60971

## Known Issues

The following is a list of known issues for PSoC Programmer 3.12.3 release.

Defect	Fix and Impact	Defect
Miniprogram1 firmware v1.77 causes an acquire failure.	In previous releases of the Miniprogram1 firmware, the reset line was pulled low during power cycle programming. The Miniprogram1 now supports devices that have active low reset line states. To account for this, the Miniprogram1 now leaves the reset line in a high-z state. Be aware of any pull up or pull down resistor circuitry that could hold the chip in a reset state.	69058
Power Cycle Mode for PSoC 3 and PSoC 5 using the Miniprogram3 is implemented with reset toggling.	The Power Cycle mode for the Miniprogram3 is currently using the reset line to acquire the target device using both SWD and JTAG protocols. A firmware solution will be available for future revisions of silicon. If development is blocked please file a tightlink support case with Cypress.	69694
CyInstaller Live Update is not supported for Windows 2000 systems.	Customers will be able to install PSoC Programmer using the CyInstaller. To update to a new version users must completely uninstall the existing version of PSoC Programmer using CyInstaller and then download the latest CyInstaller from the PSoC Programmer web page.	75099

### *Device Reorganization and Consequences:*

An update was made to the PSoC Programmer database organization that will impact customers programming certain devices using PSoC Programmer 3.12 Beta (or older) with PSoC Designer SP6 and earlier. Please see the following knowledge based article that details the issue and solution.

<http://www.cypress.com/?rid=45688>

## Limitations

The following are known limitations with PSoC Programmer:

- To program tape and reel parts chose the non tape and real part numbers (leaving off the 'T' from the marketing part number).

- You must change the programming mode manually using the provided buttons.
- The supported programming and bridging hardware can only be used by one application at a time. Closing the port in one application releases the hardware for other client applications.
- There is no programming support for wafer sale parts.
- When programming verification fails, the specific failing location(s) are not indicated.
- ICE4000 is no longer supported in PSoC Programmer.
- When using the ICE-Cube or MiniProg1 for programming, PSoC Programmer applies 3.3V to the XRES pin during connection. This may cause power to be applied to the target system. During programming, 3.3V is applied to the target system's SCLK(P1-1), SDATA (P1-0), and XRES pins.
- The MiniProg1 programmer does not support CY8C25/26xxx parts. The ICE-LPT and ICE-4000 programmers supported the CY8C25/26xxx parts. Users will need to use PSoC Programmer version 2.33 or earlier if needed.
- A very infrequent USB connection issue notifies you that an unknown device was detected when a MiniProg is plugged in. Unplugging the MiniProg1 and then reconnecting it solves this issue.
- PSoC Programmer may experience “Can't Acquire Device” errors for CYRF69103-40LFXC. There have been intermittent reports of “Can't Acquire Device” errors, which may be individually chip dependent. Programming another device clears the problem.
- If you select the Fixed Reminder option, please know that there may not be an update for PSoC Programmer currently available. Please reset the reminder interval under the Fixed Reminder, switch to an automatic web update, or disable the update reminder. Close and restart PSoC Programmer to reset the notification in the banner and in the status window.
- CY3210-MiniProg1 may have two capacitors soldered onto the SCL and SDA programming lines causing failures during programming. To remove these capacitors, please contact Cypress technical support for additional steps in addressing this issue.
- The CY3240 USB-I2C Bridge firmware cannot be upgraded in the field. Users are urged to purchase a MiniProg3 programmer-bridge, which supports USB-I2C functionality and supports field upgrades.

## Installation

### Minimum and Recommended Requirements

Hardware/Operation System Requirements	Minimum	Recommended
• Processor Speed	2 GHz	2 GHz Dual Core
• MB of RAM	2 GB	3 GB
• MB of Free Hard Drive Space	1 GB	1 GB
• Screen Resolution	1024x768	1280x1024
• CD/DVD Drive	Not Req.	✓ *
• USB	Full Speed	2.0 Hi-Speed
• Win 2000, Windows® XP (SP2 or higher), Vista, or Windows 7	✓	✓
<b>Software Prerequisites **</b>	<b>Minimum/Recommended Version</b>	
• Microsoft Internet Explorer (not IE8 beta)	7	



- .NET Framework 2.0 SP1
- Adobe Reader (for viewing PDF Documentation) 6 9+
- Windows Installer 3.1

\* CD/DVD drive is only required for installation with no web access.

### Applications Dependent on a PSoC Programmer Installation

The following applications require PSoC Programmer to be preinstalled

- PSoC Designer
- PSoC Creator

The following applications are included in the PSoC Programmer installation:

- Bridge Control Panel is selectable from PSoC Programmer CyInstaller installation
- Clock Programmer is selectable from PSoC Programmer CyInstaller installation

### Update Instructions

As part of the installation process, the Cypress Update Manager utility will also be installed and located on the **Start** menu under the Cypress folder. You can use this utility to update all programs you have installed when updates for them become available.

Follow the instructions provided by CyInstaller.

### Installation Notes

The installation process is a set of wizards that walk you through installing various components. You can install PSoC Programmer and various prerequisites from the web, or from a CD. There are slight differences in the process, based on the medium used to install the software. CyInstaller is supported by both a web installation and through an ISO image that can be downloaded and burned to a CD.

The CDs provide the necessary prerequisites and the wizards to guide you through installing the appropriate software. The Web installation requires you to download and install the executables separately. The following sections contain more specific installation details.

**Note** Do NOT plug in any programming hardware until all software installation is complete.

### Web Installation

If you are downloading the software from the web you should run the PSoC Programmer executable.

1. Double-click the PSoC Programmer executable file to launch PSoC Programmer InstallShield Wizard.
2. Install all prerequisites as needed.
3. Follow the prompts to install PSoC Programmer. The CyInstaller for PSoC Programmer opens and displays a series of steps to install PSoC Programmer and various drivers. When complete, close the installer.

Please note that some users will experience installation failure using the web installation method, this is commonly due to firewall or administration privileges. Please contact your IT individual for assistance or download the ISO image provided on the Programmer web page and burn the image and install Programmer from the CD.

## PSoC Programmer CD Installation

The PSoC Programmer ISO image contains PSoC Programmer, as well as various prerequisites.

1. Burn and Load the CD into the PC. The main installer program should run automatically. If not, double-click the cyautorun.exe file to launch it.
2. On the main installer, click the **Install Software for PSoC...** button to launch the PSoC Creator InstallShield Wizard.
3. Follow the prompts on the wizard. The first step will prompt to install PSoC Programmer.  
The CyInstaller for PSoC Programmer opens and displays a series of steps to install PSoC Programmer and various drivers.
4. Continue to follow the prompts until PSoC Programmer and the drivers are installed, and then resume with the main installer program.

## Cypress PSoC Kit CD Installation

A kit CD contains PSoC Programmer as well as additional applications such as PSoC Creator or PSoC Designer, documentation, and prerequisites needed for the associated kit. The installation process is very similar to the PSoC Programmer CD installation; however the overall process differs, as follows:

1. Load the CD. The kit installer program should run automatically. If not, double-click the autorun program to launch it.
2. On the kit installer, follow the prompts to begin the installation process. The first step will prompt to install PSoC Programmer.
3. The CyInstaller for PSoC Programmer opens and displays a series of steps to install PSoC Programmer and various drivers.
4. Continue to follow the prompts until PSoC Programmer and the drivers are installed, then resume with the kit installer program.
5. Continue the prompts to install the application IDE's, PSoC Creator or PSoC Designer. Please see the respective release notes for these tools for detailed instructions.

## Device Driver Re-Installation

During installation of PSoC Programmer you are prompted to install the device drivers for PSoC Programmer. If you clicked "Cancel" originally, and now you want to re-install the drivers, please do the following:

Navigate to the PSoC Programmer root installation directory.

Open the *Drivers* folder and run the *driver.bat* file. This installs the PSoC Programmer drivers.

## Further Reading

### Documentation

Documentation is available in the PSoC Programmer Root Directory under Documents. The documents include:

- Programmer User Guide
- PSoC Programmer COM Interface Guide
- PSoC Programmer Command Line Interface Guide

- PSoC Programmer Example Code

## Updates

Check for software updates to the Cypress PSoC development tools on the following web pages:

PSoC Software Tool	Link
PSoC Designer	<a href="http://www.cypress.com/go/psocdesigner">http://www.cypress.com/go/psocdesigner</a>
PSoC Creator	<a href="http://www.cypress.com/go/psoccreator">http://www.cypress.com/go/psoccreator</a>
PSoC Programmer	<a href="http://www.cypress.com/go/psocprogrammer">http://www.cypress.com/go/psocprogrammer</a>

## Customer Issues

We recommend that customers who experience any issues with software or PSoC devices please contact customer support at the following phone numbers 1-800-541-4736 (ext. 8) or 1-425-787-4814.

Customers may also file a Tech Support Case at the following web page:

<http://www.cypress.com/MyAccount/index.cfm?id=7&source=header>

## Silicon Errata

The most up-to-date versions of the silicon errata are available on the website at <http://www.cypress.com/psoc> under Related Documentation.





Cypress Semiconductor  
198 Champion Ct.  
San Jose, CA 95134-1709 USA  
Tel: 408.943.2600  
Fax: 408.943.4730  
Application Support Hotline: 425.787.4814  
[www.cypress.com](http://www.cypress.com)

© Cypress Semiconductor Corporation, 2010. The information contained herein is subject to change without notice. Cypress Semiconductor Corporation assumes no responsibility for the use of any circuitry other than circuitry embodied in a Cypress product. Nor does it convey or imply any license under patent or other rights. Cypress products are not warranted nor intended to be used for medical, life support, life saving, critical control or safety applications, unless pursuant to an express written agreement with Cypress. Furthermore, Cypress does not authorize its products for use as critical components in life-support systems where a malfunction or failure may reasonably be expected to result in significant injury to the user. The inclusion of Cypress products in life-support systems application implies that the manufacturer assumes all risk of such use and in doing so indemnifies Cypress against all charges.

PSoC Designer™, Programmable System-on-Chip™, and PSoC Express™ are trademarks and PSoC® is a registered trademark of Cypress Semiconductor Corp. All other trademarks or registered trademarks referenced herein are property of the respective corporations.

This Source Code (software and/or firmware) is owned by Cypress Semiconductor Corporation (Cypress) and is protected by and subject to worldwide patent protection (United States and foreign), United States copyright laws and international treaty provisions. Cypress hereby grants to licensee a personal, non-exclusive, non-transferable license to copy, use, modify, create derivative works of, and compile the Cypress Source Code and derivative works for the sole purpose of creating custom software and or firmware in support of licensee product to be used only in conjunction with a Cypress integrated circuit as specified in the applicable agreement. Any reproduction, modification, translation, compilation, or representation of this Source Code except as specified above is prohibited without the express written permission of Cypress.

Disclaimer: CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS MATERIAL, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. Cypress reserves the right to make changes without further notice to the materials described herein. Cypress does not assume any liability arising out of the application or use of any product or circuit described herein. Cypress does not authorize its products for use as critical components in life-support systems where a malfunction or failure may reasonably be expected to result in significant injury to the user. The inclusion of Cypress' product in a life-support systems application implies that the manufacturer assumes all risk of such use and in doing so indemnifies Cypress against all charges.

Use may be limited by and subject to the applicable Cypress software license agreement.

---