



---

The following document contains information on Cypress products. Although the document is marked with the name "Spansion" and "Fujitsu", the company that originally developed the specification, Cypress will continue to offer these products to new and existing customers.

#### **Continuity of Specifications**

There is no change to this document as a result of offering the device as a Cypress product. Any changes that have been made are the result of normal document improvements and are noted in the document history page, where supported. Future revisions will occur when appropriate, and changes will be noted in a document history page.

#### **Continuity of Ordering Part Numbers**

Cypress continues to support existing part numbers. To order these products, please use only the Ordering Part Numbers listed in this document.

#### **For More Information**

Please contact your local sales office for additional information about Cypress products and solutions.

#### **About Cypress**

Cypress (NASDAQ: CY) delivers high-performance, high-quality solutions at the heart of today's most advanced embedded systems, from automotive, industrial and networking platforms to highly interactive consumer and mobile devices. With a broad, differentiated product portfolio that includes NOR flash memories, F-RAM™ and SRAM, Traveo™ microcontrollers, the industry's only PSoC® programmable system-on-chip solutions, analog and PMIC Power Management ICs, CapSense® capacitive touch-sensing controllers, and Wireless BLE Bluetooth® Low-Energy and USB connectivity solutions, Cypress is committed to providing its customers worldwide with consistent innovation, best-in-class support and exceptional system value.

## Errata

This errata sheet is for MB90560/565 Series Data Sheet Rev.5 (DS07-13715-5E)

F<sup>2</sup>MC-16LX  
16-BIT MICROCONTROLLER  
MB90560/565 Series  
DATA SHEET

2011.8.2

Date	Page	Item	Description																																																																	
2011/8/2	59	■ ELECTRICAL CHARACTERISTICS (MB90560 SERIES) 4. AC Characteristics	(1) Clock Timings was changed as indicated by the shading below.																																																																	
			(Error)																																																																	
			<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th rowspan="2">Parameter</th> <th rowspan="2">Symbol</th> <th rowspan="2">Pin Name</th> <th rowspan="2">Condition</th> <th colspan="3">Value</th> <th rowspan="2">Unit</th> <th rowspan="2">Remarks</th> </tr> <tr> <th>Min.</th> <th>Typ.</th> <th>Max.</th> </tr> </thead> <tbody> <tr> <td rowspan="2">Clock frequency</td> <td rowspan="2">f<sub>C</sub></td> <td rowspan="2">X0, X1</td> <td rowspan="2">-</td> <td>3</td> <td>-</td> <td>16</td> <td rowspan="2">MHz</td> <td>With a PLL circuit</td> </tr> <tr> <td>1</td> <td>-</td> <td>16</td> <td>Without a PLL circuit</td> </tr> <tr> <td>Internal operating clock frequency</td> <td>f<sub>CP</sub></td> <td>-</td> <td>-</td> <td>1.5</td> <td>-</td> <td>16</td> <td>MHz</td> <td>When using a main clock</td> </tr> <tr> <td>Internal operating clock cycle time</td> <td>t<sub>CP</sub></td> <td>-</td> <td>-</td> <td>62.5</td> <td>-</td> <td>333</td> <td>ns</td> <td>When using a main clock</td> </tr> </tbody> </table>							Parameter	Symbol	Pin Name	Condition	Value			Unit	Remarks	Min.	Typ.	Max.	Clock frequency	f <sub>C</sub>	X0, X1	-	3	-	16	MHz	With a PLL circuit	1	-	16	Without a PLL circuit	Internal operating clock frequency	f <sub>CP</sub>	-	-	1.5	-	16	MHz	When using a main clock	Internal operating clock cycle time	t <sub>CP</sub>	-	-	62.5	-	333	ns	When using a main clock																
Parameter	Symbol	Pin Name	Condition	Value			Unit	Remarks																																																												
				Min.	Typ.	Max.																																																														
Clock frequency	f <sub>C</sub>	X0, X1	-	3	-	16	MHz	With a PLL circuit																																																												
				1	-	16		Without a PLL circuit																																																												
Internal operating clock frequency	f <sub>CP</sub>	-	-	1.5	-	16	MHz	When using a main clock																																																												
Internal operating clock cycle time	t <sub>CP</sub>	-	-	62.5	-	333	ns	When using a main clock																																																												
			(Correct)																																																																	
			<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th rowspan="2">Parameter</th> <th rowspan="2">Symbol</th> <th rowspan="2">Pin Name</th> <th rowspan="2">Condition</th> <th colspan="3">Value</th> <th rowspan="2">Unit</th> <th rowspan="2">Remarks</th> </tr> <tr> <th>Min.</th> <th>Typ.</th> <th>Max.</th> </tr> </thead> <tbody> <tr> <td rowspan="6">Clock frequency</td> <td rowspan="6">f<sub>C</sub></td> <td rowspan="6">X0, X1</td> <td rowspan="6">-</td> <td>1</td> <td>-</td> <td>16</td> <td rowspan="6">MHz</td> <td>Multiplied none with a Internal oscillator circuit</td> </tr> <tr> <td>3</td> <td>-</td> <td>16</td> <td>1 multiplied PLL with a Internal oscillator circuit</td> </tr> <tr> <td>3</td> <td>-</td> <td>8</td> <td>2 multiplied PLL with a Internal oscillator circuit</td> </tr> <tr> <td>3</td> <td>-</td> <td>5.3</td> <td>3 multiplied PLL with a Internal oscillator circuit</td> </tr> <tr> <td>3</td> <td>-</td> <td>4</td> <td>4 multiplied PLL with a Internal oscillator circuit</td> </tr> <tr> <td>1</td> <td>-</td> <td>16</td> <td>Without a PLL circuit</td> </tr> <tr> <td>Internal operating clock frequency</td> <td>f<sub>CP</sub></td> <td>-</td> <td>-</td> <td>0.5</td> <td>-</td> <td>16</td> <td>MHz</td> <td>When using a main clock</td> </tr> <tr> <td>Internal operating clock cycle time</td> <td>t<sub>CP</sub></td> <td>-</td> <td>-</td> <td>62.5</td> <td>-</td> <td>2000</td> <td>ns</td> <td>When using a main clock</td> </tr> </tbody> </table>							Parameter	Symbol	Pin Name	Condition	Value			Unit	Remarks	Min.	Typ.	Max.	Clock frequency	f <sub>C</sub>	X0, X1	-	1	-	16	MHz	Multiplied none with a Internal oscillator circuit	3	-	16	1 multiplied PLL with a Internal oscillator circuit	3	-	8	2 multiplied PLL with a Internal oscillator circuit	3	-	5.3	3 multiplied PLL with a Internal oscillator circuit	3	-	4	4 multiplied PLL with a Internal oscillator circuit	1	-	16	Without a PLL circuit	Internal operating clock frequency	f <sub>CP</sub>	-	-	0.5	-	16	MHz	When using a main clock	Internal operating clock cycle time	t <sub>CP</sub>	-	-	62.5	-	2000	ns	When using a main clock
Parameter	Symbol	Pin Name	Condition	Value			Unit	Remarks																																																												
				Min.	Typ.	Max.																																																														
Clock frequency	f <sub>C</sub>	X0, X1	-	1	-	16	MHz	Multiplied none with a Internal oscillator circuit																																																												
				3	-	16		1 multiplied PLL with a Internal oscillator circuit																																																												
				3	-	8		2 multiplied PLL with a Internal oscillator circuit																																																												
				3	-	5.3		3 multiplied PLL with a Internal oscillator circuit																																																												
				3	-	4		4 multiplied PLL with a Internal oscillator circuit																																																												
				1	-	16		Without a PLL circuit																																																												
Internal operating clock frequency	f <sub>CP</sub>	-	-	0.5	-	16	MHz	When using a main clock																																																												
Internal operating clock cycle time	t <sub>CP</sub>	-	-	62.5	-	2000	ns	When using a main clock																																																												
			[mcu doc1012,1013,1014]																																																																	

Date	Page	Item	Description
2011/8/2	60	■ ELECTRICAL CHARACTERISTICS (MB90560 SERIES) 4. AC Characteristics	<p>Internal Clock <math>f_{CP}</math> (MHz) of PLL guaranteed operation range was changed as indicated by the shading below.</p> <p>(Error)</p> <p>(Correct)</p> <p>[mcu doc1018]</p>

Date	Page	Item	Description																																						
2011/8/2	62	<p>■ ELECTRICAL CHARACTERISTICS (MB90560 SERIES)</p> <p>4. AC Characteristics</p>	<p>(3) Power-On Reset as indicated by the shading below.</p> <p>(Error)</p> <table border="1"> <thead> <tr> <th rowspan="2">Parameter</th> <th rowspan="2">Symbol</th> <th rowspan="2">Pin Name</th> <th rowspan="2">Condition</th> <th colspan="2">Value</th> <th rowspan="2">Unit</th> <th rowspan="2">Remarks</th> </tr> <tr> <th>Min.</th> <th>Max.</th> </tr> </thead> <tbody> <tr> <td>Power supply cutoff time</td> <td>t<sub>OFF</sub></td> <td>V<sub>CC</sub></td> <td>-</td> <td>4</td> <td>-</td> <td>ms</td> <td>For repeated operation</td> </tr> </tbody> </table> <p>(Correct)</p> <table border="1"> <thead> <tr> <th rowspan="2">Parameter</th> <th rowspan="2">Symbol</th> <th rowspan="2">Pin Name</th> <th rowspan="2">Condition</th> <th colspan="2">Value</th> <th rowspan="2">Unit</th> <th rowspan="2">Remarks</th> </tr> <tr> <th>Min.</th> <th>Max.</th> </tr> </thead> <tbody> <tr> <td>Power supply cutoff time</td> <td>t<sub>OFF</sub></td> <td>V<sub>CC</sub></td> <td>-</td> <td>4</td> <td>-</td> <td>ms</td> <td>Waiting time to power-on precautions</td> </tr> </tbody> </table> <p>[mcu_doc1015]</p>	Parameter	Symbol	Pin Name	Condition	Value		Unit	Remarks	Min.	Max.	Power supply cutoff time	t <sub>OFF</sub>	V <sub>CC</sub>	-	4	-	ms	For repeated operation	Parameter	Symbol	Pin Name	Condition	Value		Unit	Remarks	Min.	Max.	Power supply cutoff time	t <sub>OFF</sub>	V <sub>CC</sub>	-	4	-	ms	Waiting time to power-on precautions		
Parameter	Symbol	Pin Name	Condition					Value				Unit	Remarks																												
				Min.	Max.																																				
Power supply cutoff time	t <sub>OFF</sub>	V <sub>CC</sub>	-	4	-	ms	For repeated operation																																		
Parameter	Symbol	Pin Name	Condition	Value		Unit	Remarks																																		
				Min.	Max.																																				
Power supply cutoff time	t <sub>OFF</sub>	V <sub>CC</sub>	-	4	-	ms	Waiting time to power-on precautions																																		
2011/8/2	66	<p>■ ELECTRICAL CHARACTERISTICS (MB90560 SERIES)</p> <p>5. Electrical Characteristics for the A/D Converter</p>	<p>Reference voltage as indicated by the shading below.</p> <p>(Error)</p> <table border="1"> <thead> <tr> <th rowspan="2">Parameter</th> <th rowspan="2">Symbol</th> <th rowspan="2">Pin Name</th> <th colspan="3">Value</th> <th rowspan="2">Unit</th> <th rowspan="2">Remarks</th> </tr> <tr> <th>Min.</th> <th>Typ.</th> <th>Max.</th> </tr> </thead> <tbody> <tr> <td>Reference voltage</td> <td>-</td> <td>AVR</td> <td>2.7</td> <td>-</td> <td>AV<sub>CC</sub></td> <td>V</td> <td></td> </tr> </tbody> </table> <p>(Correct)</p> <table border="1"> <thead> <tr> <th rowspan="2">Parameter</th> <th rowspan="2">Symbol</th> <th rowspan="2">Pin Name</th> <th colspan="3">Value</th> <th rowspan="2">Unit</th> <th rowspan="2">Remarks</th> </tr> <tr> <th>Min.</th> <th>Typ.</th> <th>Max.</th> </tr> </thead> <tbody> <tr> <td>Reference voltage</td> <td>-</td> <td>AVR</td> <td>3.0</td> <td>-</td> <td>AV<sub>CC</sub></td> <td>V</td> <td></td> </tr> </tbody> </table> <p>[mcu_doc1017]</p>	Parameter	Symbol	Pin Name	Value			Unit	Remarks	Min.	Typ.	Max.	Reference voltage	-	AVR	2.7	-	AV <sub>CC</sub>	V		Parameter	Symbol	Pin Name	Value			Unit	Remarks	Min.	Typ.	Max.	Reference voltage	-	AVR	3.0	-	AV <sub>CC</sub>	V	
Parameter	Symbol	Pin Name	Value				Unit	Remarks																																	
			Min.	Typ.	Max.																																				
Reference voltage	-	AVR	2.7	-	AV <sub>CC</sub>	V																																			
Parameter	Symbol	Pin Name	Value			Unit	Remarks																																		
			Min.	Typ.	Max.																																				
Reference voltage	-	AVR	3.0	-	AV <sub>CC</sub>	V																																			
2011/8/2	75	<p>■ ELECTRICAL CHARACTERISTICS (MB90565 SERIES)</p> <p>4. AC Characteristics</p>	<p>(3) Power-On Reset as indicated by the shading below.</p> <p>(Error)</p> <table border="1"> <thead> <tr> <th rowspan="2">Parameter</th> <th rowspan="2">Symbol</th> <th rowspan="2">Pin Name</th> <th rowspan="2">Condition</th> <th colspan="2">Value</th> <th rowspan="2">Unit</th> <th rowspan="2">Remarks</th> </tr> <tr> <th>Min.</th> <th>Max.</th> </tr> </thead> <tbody> <tr> <td>Power supply cutoff time</td> <td>t<sub>OFF</sub></td> <td>V<sub>CC</sub></td> <td>-</td> <td>4</td> <td>-</td> <td>ms</td> <td>For repeated operation</td> </tr> </tbody> </table> <p>(Correct)</p> <table border="1"> <thead> <tr> <th rowspan="2">Parameter</th> <th rowspan="2">Symbol</th> <th rowspan="2">Pin Name</th> <th rowspan="2">Condition</th> <th colspan="2">Value</th> <th rowspan="2">Unit</th> <th rowspan="2">Remarks</th> </tr> <tr> <th>Min.</th> <th>Max.</th> </tr> </thead> <tbody> <tr> <td>Power supply cutoff time</td> <td>t<sub>OFF</sub></td> <td>V<sub>CC</sub></td> <td>-</td> <td>4</td> <td>-</td> <td>ms</td> <td>Waiting time to power-on precautions</td> </tr> </tbody> </table> <p>[mcu_doc1016]</p>	Parameter	Symbol	Pin Name	Condition	Value		Unit	Remarks	Min.	Max.	Power supply cutoff time	t <sub>OFF</sub>	V <sub>CC</sub>	-	4	-	ms	For repeated operation	Parameter	Symbol	Pin Name	Condition	Value		Unit	Remarks	Min.	Max.	Power supply cutoff time	t <sub>OFF</sub>	V <sub>CC</sub>	-	4	-	ms	Waiting time to power-on precautions		
Parameter	Symbol	Pin Name	Condition					Value				Unit	Remarks																												
				Min.	Max.																																				
Power supply cutoff time	t <sub>OFF</sub>	V <sub>CC</sub>	-	4	-	ms	For repeated operation																																		
Parameter	Symbol	Pin Name	Condition	Value		Unit	Remarks																																		
				Min.	Max.																																				
Power supply cutoff time	t <sub>OFF</sub>	V <sub>CC</sub>	-	4	-	ms	Waiting time to power-on precautions																																		